

Starting Out With AIPS Tutorial

James M Anderson

This tutorial session is intended to get people familiar with the basic concepts of radio interferometry. The student will be introduced to interferometry data, visibilities, the (u,v) plane, calibration, and imaging.

Step 1 --- Figure Out What to Observe (Reduce)

I decided to try to make an image of the Sun, as the Solar KSP is a significant part of GLOW. The NRAO image archive has a nice image of the Sun at 1400 MHz located at <http://images.nrao.edu/8>



Image courtesy of NRAO/AUI

Let's try to reduce the data ourselves.

Step 2 --- Download the Data From the Archive

Conveniently, the NRAO image archive gives details about the observations used to make the image, so I downloaded the data from the NRAO data archive, making sure to select the "AIPS friendly" filename option.

This has resulted in two files on my hard drive in my current directory:

```
ls -l
total 54164
-rw-r-- 1 anderson zeall 21002240 2008-11-11 14:40 GD_1
-rw-r-- 1 anderson zeall 34392064 2008-11-11 14:41 GD_2
```

Step 3 --- Start up AIPS

aips

I have chosen to use user ID 100, at semi-random selection.

At first, most of the arcane syntax used to enter commands to AIPS will be difficult. As this is a tutorial session which intends to teach you about radio interferometry, and not how to use AIPS, we will gloss over the technical challenges of interacting with AIPS.

In AIPS you the user interact with something called POPS. You give POPS information by setting variables called ADVERBS to specific values. You can tell POPS which TASK you plan to run by setting a TASK ADVERB. If you want to check the values of ADVERBs for the current TASK, you ask for INPUTS. Because POPS will try to figure out what you mean if you only input the first few letters of an ADVERB or VERB, you can often abbreviate this to just INP. Also note that since AIPS is case-insensitive by default, you could also just type inp. If you want help on a specific topic, ask for HELP. If you want even more explanation for something, say EXPLAIN. If you don't know what it is you are trying to do, but you have some vague notion, say APROPOS SOMETHING. Note that apostrophes, and in certain locations, the lack of an apostrophe are significant.

Step 4 --- Initial look at data

FILLM

The AIPS task to read raw VLA data into AIPS is called FILLM.

```
dowait=true
dohist=1
docrt=132
dotv=1
task 'fillm'
default
datain = 'PWD:GD_
nfiles=0
ncount=2
vlamode='S '
doweight=10
doconcat=true
douvcomp=0
cparm(2)=16
cparm(4)=28
cparm(8)=10./60
go
```

This sets us up to read the data, sets the VLA mode to Solar, tells AIPS not to change the source if the position appears to be moving (which the Sun does), sets the shadowing limit to 28 meters, and sets the CL table interval to 10 seconds.

Header information

pcat

```
AIPS 1: Catalog on disk 1
AIPS 1:  Cat Usid Mapname      Class  Seq  Pt      Last access      Stat
AIPS 1:    1  100 19810926     .L BAND.      1 UV 14-NOV-2008 21:35:31
```

getn 2

imhe

```
AIPS 1: Image=MULTI      (UV)      Filename=19810926     .L BAND.    1
AIPS 1: Telescope=VLA      Receiver=VLA
AIPS 1: Observer=GD      User #= 100
AIPS 1: Observ. date=26-SEP-1981    Map date=14-NOV-2008
AIPS 1: # visibilities    556884    Sort order  TB
AIPS 1: Rand axes: UU-L-SIN  VV-L-SIN  WW-L-SIN  BASELINE  TIME1
AIPS 1:      SOURCE  FREQSEL
AIPS 1: -----
AIPS 1: Type      Pixels  Coord value      at Pixel      Coord incr  Rotat
AIPS 1: COMPLEX      3    1.0000000E+00      1.00    1.0000000E+00    0.00
AIPS 1: STOKES      4   -1.0000000E+00      1.00   -1.0000000E+00    0.00
AIPS 1: FREQ      1    1.4461500E+09      1.00    1.2500000E+07    0.00
AIPS 1: IF      1    1.0000000E+00      1.00    1.0000000E+00    0.00
AIPS 1: RA      1      00 00 00.000      1.00      3600.000    0.00
AIPS 1: DEC      1      00 00 00.000      1.00      3600.000    0.00
AIPS 1: -----
AIPS 1: Coordinate equinox    0.00
AIPS 1: Maximum version number of extension files of type HI is 1
AIPS 1: Maximum version number of extension files of type AN is 1
AIPS 1: Maximum version number of extension files of type NX is 1
AIPS 1: Maximum version number of extension files of type SU is 1
AIPS 1: Maximum version number of extension files of type FQ is 1
AIPS 1: Maximum version number of extension files of type CL is 1
AIPS 1: Maximum version number of extension files of type TY is 1
AIPS 1: Maximum version number of extension files of type WX is 1
AIPS 1: Maximum version number of extension files of type OF is 1
AIPS 1: Keyword = 'CORRMODE' value = '
AIPS 1: Keyword = 'VLAIFS ' value = 'AC
AIPS 1: Keyword = 'CORRCOEF' value = -1
```

LISTR --- scan listing

First, let's check out which file we need.

pcat

```
AIPS 1: Catalog on disk 1
AIPS 1:  Cat Usid Mapname      Class  Seq  Pt      Last access      Stat
AIPS 1:    1  100 19810926     .C BAND.      1 UV 11-NOV-2008 18:44:06
AIPS 1:    2  100 19810926     .L BAND.      1 UV 11-NOV-2008 18:46:44
```

AIPS 1:	3	100	19810926	.C BAND.	2 UV	11-NOV-2008	18:40:21
AIPS 1:	4	100	19810926	.L BAND.	2 UV	11-NOV-2008	18:40:21

```
default listr
task 'listr'
indi 1
getn 2
optype 'scan'
docrt=132
go
```

```
AIPS 1: Got(1)   disk= 1  user= 100   type=UV   19810926.L BAND.1
vlb054   LISTR(31DEC08)   100      11-NOV-2008  18:46:44   Page    1
File = 19810926   .L BAND.   1 Vol = 1  Userid =   100
Freq = 1.446150006 GHz  Ncor =  4   No. vis =   278465
Scan summary listing
```

Scan	Source	Qual	Calcode	Sub	Timerange	FrqID
START VIS	END VIS					
1 1148-001		: 0000	C	1	0/13:53:25 - 0/13:54:35	1
1	2195					
2 SUN		: 0000		1	0/13:59:15 - 0/13:59:35	1
2196	3150					
3 1148-001		: 0000	C	1	0/14:18:05 - 0/14:19:35	1
3151	5809					
4 SUN		: 0000		1	0/14:20:25 - 0/14:24:35	1
5810	14662					
5 1148-001		: 0000	C	1	0/14:43:05 - 0/14:44:35	1
14663	17320					
6 SUN		: 0000		1	0/14:45:25 - 0/14:49:35	1
17321	25867					
7 1148-001		: 0000	C	1	0/15:07:55 - 0/15:09:25	1
25868	28503					
8 SUN		: 0000		1	0/15:10:15 - 0/15:14:25	1
28504	37058					
9 1148-001		: 0000	C	1	0/15:32:55 - 0/15:34:25	1
37059	39716					
10 SUN		: 0000		1	0/15:35:15 - 0/15:39:25	1
39717	48338					
11 1148-001		: 0000	C	1	0/15:57:55 - 0/15:59:25	1
48339	50720					
12 SUN		: 0000		1	0/16:00:15 - 0/16:04:15	1
50721	58994					
13 1148-001		: 0000	C	1	0/16:22:45 - 0/16:24:15	1
58995	61584					
14 SUN		: 0000		1	0/16:25:05 - 0/16:29:15	1
61585	70334					
15 1148-001		: 0000	C	1	0/16:47:45 - 0/16:49:15	1
70335	72949					

16 SUN	: 0000	1	0/16:50:05 - 0/16:54:15	1
72950 81664				
17 1148-001	: 0000 C	1	0/17:12:35 - 0/17:12:35	1
81665 81664				
18 1148-001	: 0000 C	1	0/17:12:45 - 0/17:14:05	1
81665 84070				
19 SUN	: 0000	1	0/17:14:55 - 0/17:19:05	1
84071 92937				
20 1148-001	: 0000 C	1	0/17:37:35 - 0/17:39:05	1
92938 95507				
21 SUN	: 0000	1	0/17:39:45 - 0/17:44:25	1
95508 105079				
22 1148-001	: 0000 C	1	0/18:02:25 - 0/18:03:55	1
105080 107535				
23 SUN	: 0000	1	0/18:04:45 - 0/18:08:55	1
107536 116401				
24 1148-001	: 0000 C	1	0/18:27:25 - 0/18:28:55	1
116402 119012				
25 SUN	: 0000	1	0/18:29:45 - 0/18:33:55	1
119013 127842				
26 1148-001	: 0000 C	1	0/18:52:35 - 0/18:53:55	1
127843 129825				
27 SUN	: 0000	1	0/18:54:45 - 0/18:59:05	1
129826 137705				
28 1148-001	: 0000 C	1	0/19:17:25 - 0/19:18:45	1
137706 139972				
29 SUN	: 0000	1	0/19:19:35 - 0/19:23:45	1
139973 148118				
30 1148-001	: 0000 C	1	0/19:42:15 - 0/19:43:45	1
148119 150467				
31 SUN	: 0000	1	0/19:44:35 - 0/19:53:05	1
150468 168022				
32 1148-001	: 0000 C	1	0/20:07:05 - 0/20:08:35	1
168023 170342				
33 SUN	: 0000	1	0/20:09:25 - 0/20:13:35	1
170343 178889				
34 1148-001	: 0000 C	1	0/20:32:05 - 0/20:33:35	1
178890 181422				
35 SUN	: 0000	1	0/20:34:25 - 0/20:38:35	1
181423 190047				
36 1148-001	: 0000 C	1	0/20:57:05 - 0/20:58:35	1
190048 192547				
37 SUN	: 0000	1	0/20:59:25 - 0/21:03:35	1
192548 201271				
38 1148-001	: 0000 C	1	0/21:21:55 - 0/21:23:25	1
201272 203709				
39 SUN	: 0000	1	0/21:24:15 - 0/21:28:25	1
203710 212708				
40 1148-001	: 0000 C	1	0/21:47:05 - 0/21:48:25	1
212709 215193				
41 SUN	: 0000	1	0/21:49:15 - 0/21:53:25	1

215194	224112						
42	1148-001	:	0000	C	1	0/22:11:45 - 0/22:13:15	1
224113	226323						
43	SUN	:	0000		1	0/22:14:05 - 0/22:18:15	1
226324	234634						
44	1148-001	:	0000	C	1	0/22:36:55 - 0/22:38:15	1
234635	236916						
45	SUN	:	0000		1	0/22:39:05 - 0/22:43:15	1
236917	245740						
46	1148-001	:	0000	C	1	0/23:01:55 - 0/23:03:15	1
245741	248122						
47	SUN	:	0000		1	0/23:04:05 - 0/23:08:05	1
248123	256112						
48	1148-001	:	0000	C	1	0/23:26:45 - 0/23:28:05	1
256113	258141						
49	SUN	:	0000		1	0/23:28:55 - 0/23:33:05	1
258142	265941						
50	1148-001	:	0000	C	1	0/23:51:45 - 0/23:53:05	1
265942	267662						
51	SUN	:	0000		1	0/23:54:05 - 0/23:58:05	1
267663	275388						
52	SUN	:	0000		1	1/00:07:25 - 1/00:07:55	1
275389	276069						
53	3C286	:	0000	B	1	1/00:21:35 - 1/00:22:55	1
276070	278465						

Source summary

Velocity type = ' ' Definition = ' '

ID	Source	Qual	Calcode	RA(0.0)	Dec(0.0)	IFlux
QFlux	UFlux	VFlux	No. vis			
1	1148-001	:	0000	C	11:48:10.1300 -00:07:13.300	0.000
0.000	0.000	0.000	59936			
2	SUN	:	0000		12:10:30.1272 -01:08:22.648	0.000
0.000	0.000	0.000	216133			
3	3C286	:	0000	B	13:28:49.6570 30:45:58.640	0.000
0.000	0.000	0.000	2396			

ID	Source	Freq(GHz)	Velocity(Km/s)	Rest freq (GHz)
1	All Sources	1.4462	0.0000	0.0000

Frequency Table summary

FQID	IF#	Freq(GHz)	BW(kHz)	Ch.Sep(kHz)	Sideband
1	1	1.44615001	12500.0010	12500.0010	1

AIPS 1: Resumes

getn 4
go

AIPS 1: Got(1) disk= 1 user= 100 type=UV 19810926.L BAND.2
 vlb054 LISTR(31DEC08) 100 11-NOV-2008 18:49:17 Page 1
 File = 19810926 .L BAND. 2 Vol = 1 Userid = 100
 Freq = 1.446150006 GHz Ncor = 4 No. vis = 207072
 Scan summary listing

Scan	Source	Qual	Calcode	Sub	Timerange	FrqID
START VIS	END VIS					
1 SUN		: 0000		1	0/14:05:15 - 0/14:09:35	1
1	8935					
2 SUN		: 0000		1	0/14:30:05 - 0/14:34:35	1
8936	17885					
3 SUN		: 0000		1	0/14:55:05 - 0/14:59:25	1
17886	26458					
4 SUN		: 0000		1	0/15:19:55 - 0/15:24:25	1
26459	35408					
5 SUN		: 0000		1	0/15:44:55 - 0/15:49:25	1
35409	44108					
6 SUN		: 0000		1	0/16:09:45 - 0/16:14:15	1
44109	52834					
7 SUN		: 0000		1	0/16:34:45 - 0/16:39:15	1
52835	61669					
8 SUN		: 0000		1	0/16:59:45 - 0/17:04:05	1
61670	70226					
9 SUN		: 0000		1	0/17:24:35 - 0/17:29:05	1
70227	79180					
10 SUN		: 0000		1	0/17:50:15 - 0/17:54:05	1
79181	86877					
11 SUN		: 0000		1	0/18:14:25 - 0/18:18:55	1
86878	95785					
12 SUN		: 0000		1	0/18:39:35 - 0/18:44:05	1
95786	104689					
13 SUN		: 0000		1	0/19:04:25 - 0/19:08:45	1
104690	112638					
14 SUN		: 0000		1	0/19:29:15 - 0/19:33:45	1
112639	120854					
15 SUN		: 0000		1	0/19:54:25 - 0/19:58:45	1
120855	128861					
16 SUN		: 0000		1	0/20:19:05 - 0/20:23:35	1
128862	137749					
17 SUN		: 0000		1	0/20:44:05 - 0/20:48:35	1
137750	146600					
18 SUN		: 0000		1	0/21:08:55 - 0/21:13:25	1
146601	155488					
19 SUN		: 0000		1	0/21:33:55 - 0/21:38:25	1
155489	164306					
20 SUN		: 0000		1	0/21:58:55 - 0/22:03:25	1
164307	173005					
21 SUN		: 0000		1	0/22:23:55 - 0/22:28:15	1
173006	181479					
22 SUN		: 0000		1	0/22:48:55 - 0/22:53:25	1

181480	190299						
23 SUN		: 0000	1	0/23:13:45	-	0/23:18:05	1
190300	199102						
24 SUN		: 0000	1	0/23:38:45	-	0/23:43:05	1
199103	207072						
25 SUN		: 0000	1	1/00:01:15	-	1/00:01:15	1
207073	207072						
Source summary							
Velocity type = ' ' Definition = ' '							
ID Source Qual Calcode RA(0.0) Dec(0.0) IFlux							
QFlux	UFlux	VFlux	No. vis				
1 SUN		: 0000		12:10:30.1272	-01:08:22.648	0.000	
0.000	0.000	0.000	207072				
ID Source Freq(GHz) Velocity(Km/s) Rest freq (GHz)							
1 All Sources		1.4462	0.0000	0.0000			
Frequency Table summary							
FQID	IF#	Freq(GHz)	BW(kHz)	Ch.Sep(kHz)	Sideband		
1	1	1.44615001	12500.0010	12500.0010	1		
AIPS 1: Resumes							

PRTAN

Print the Antenna positions — useful for thinking about calibration.

```
getn 2
go prtan
```

vlb054	PRTAN(31DEC08)	100	11-NOV-2008	18:53:09	Page	1
File=19810926	.L BAND.	1	An.ver= 1	Vol= 1	User=	100
Array= VLA	Freq=	1446.150006 MHz	Ref.date=	26-SEP-1981		
Array reference position in meters (Earth centered)						
Array BX=	-1601185.36500	BY=	-5041977.54700	BZ=	3554875.87000	
Polar X =	0.00000	Polar Y =	0.00000	arcsec		
Earth rotation rate = 360.9856449713 degrees / IAT day						
GST at UT=0 = 364.7139688925 degrees						
UT1-UTC=	0.0000000	Data time(IAT	)	-UTC=	0.0000000	seconds
Solutions not yet determined for a particular FREQID						
Ant 1 = VLA:_N2	BX=	-30.0602	BY=	-4.7835	BZ=	45.7022
Mount=ALAZ	Axis offset=	0.0000 meters	IFA		IFB	
Feed polarization type =			R		L	
Ant 2 = VLA:_E5	BX=	51.8719	BY=	195.8466	BZ=	-75.1013

Mount=ALAZ Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =	R	L
Ant 3 = VLA:_E9 BX= 139.6430 BY= 536.8956 BZ= -207.7424		
Mount=ALAZ Axis offset= -0.0033 meters	IFA	IFB
Feed polarization type =	R	L
Ant 4 = VLA:_E6 BX= 70.6548 BY= 267.7575 BZ= -102.8996		
Mount=ALAZ Axis offset= 0.0078 meters	IFA	IFB
Feed polarization type =	R	L
Ant 5 = VLA:_N3 BX= -52.4373 BY= -8.2629 BZ= 78.6643		
Mount=ALAZ Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =	R	L
Ant 6 = VLA:_W2 BX= 14.7735 BY= -37.1404 BZ= -20.2135		
Mount=ALAZ Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =	R	L
Ant 7 = VLA:_W3 BX= 28.9195 BY= -74.4876 BZ= -41.0524		
Mount=ALAZ Axis offset= -0.0036 meters	IFA	IFB
Feed polarization type =	R	L
Ant 8 = VLA:_W1 BX= 22.9920 BY= 3.4974 BZ= -32.4864		
Mount=ALAZ Axis offset= 0.0084 meters	IFA	IFB
Feed polarization type =	R	L
Ant 9 = VLA:_E2 BX= 11.3328 BY= 40.6638 BZ= -15.1624		
Mount=ALAZ Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =	R	L
Ant 10 = VLA:_OUT BX= 0.0000 BY= 0.0000 BZ= 0.0000		
Mount=ALAZ Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =	R	L
Ant 11 = VLA:_E8 BX= 114.4257 BY= 438.6941 BZ= -169.4880		
Mount=ALAZ Axis offset= 0.0048 meters	IFA	IFB
Feed polarization type =	R	L
Ant 12 = VLA:_E3 BX= 21.9945 BY= 81.5250 BZ= -30.9498		
Mount=ALAZ Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =	R	L
Ant 13 = VLA:_E7 BX= 91.5227 BY= 348.8871 BZ= -134.4449		
Mount=ALAZ Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =	R	L
Ant 14 = VLA:_W7 BX= 121.6261 BY= -319.1264 BZ= -177.5842		
Mount=ALAZ Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =	R	L

Ant 15 = VLA:_W9	BX= 186.8061	BY= -491.1158	BZ= -273.5624
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 16 = VLA:_E4	BX= 35.6150	BY= 133.6310	BZ= -51.1099
Mount=ALAZ	Axis offset= -0.0051 meters	IFA	IFB
Feed polarization type =		R	L
Ant 17 = VLA:_W8	BX= 152.7524	BY= -401.2839	BZ= -223.4146
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 18 = VLA:_E1	BX= 45.3386	BY= 7.0026	BZ= -65.4888
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 19 = VLA:_N7	BX= -193.6105	BY= -30.2503	BZ= 286.4580
Mount=ALAZ	Axis offset= -0.0030 meters	IFA	IFB
Feed polarization type =		R	L
Ant 20 = VLA:_N1	BX= 0.6703	BY= 0.0144	BZ= 0.5135
Mount=ALAZ	Axis offset= 0.0045 meters	IFA	IFB
Feed polarization type =		R	L
Ant 21 = VLA:_N8	BX= -243.6039	BY= -38.0389	BZ= 360.0340
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 22 = VLA:_W5	BX= 68.6012	BY= -179.2282	BZ= -99.5242
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 23 = VLA:_N5	BX= -108.4301	BY= -16.9862	BZ= 161.0152
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 24 = VLA:_N9	BX= -298.3837	BY= -46.5620	BZ= 440.6260
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 25 = VLA:_N6	BX= -148.4545	BY= -23.2162	BZ= 219.9871
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 26 = VLA:_N4	BX= -74.8318	BY= -11.7331	BZ= 111.6208
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB
Feed polarization type =		R	L
Ant 27 = VLA:_W6	BX= 93.5170	BY= -245.0012	BZ= -136.2284
Mount=ALAZ	Axis offset= 0.0000 meters	IFA	IFB

```

Feed polarization type =           R           L

Ant 28 = VLA:_W4 BX=          46.9220 BY=      -122.0267 BZ=      -67.6047
Mount=ALAZ Axis offset=  0.0000 meters   IFA           IFB
Feed polarization type =           R           L

Ant 29 = VPT:_OUT BX=           0.0000 BY=           0.0000 BZ=           0.0000
Mount=ALAZ Axis offset=  0.0000 meters   IFA           IFB
Feed polarization type =           R           L

```

Location Of VLA Antennas

```

          N9 (24)
          N8 (21)
          N7 (19)
          N6 (25)
          N5 (23)
          N4 (26)
          N3 ( 5)
          N2 ( 1)
          N1 (20)
      ( 8) W1   E1 (18)
    ( 6) W2     E2 ( 9)
  ( 7) W3       E3 (12)
(28) W4         E4 (16)
(22) W5         E5 ( 2)
(27) W6         E6 ( 4)
(14) W7         E7 (13)
(17) W8         E8 (11)
(15) W9         E9 ( 3)

          VLA:_OUT (10)
          VPT:_OUT (29)

```

AIPS 1: Resumes

SETJY

```

task 'setjy'
source '3c286',' '
optype 'calc'
aparm(2)=3
go

```

```

vlb054> SETJY1: Task SETJY (release of 31DEC08) begins
vlb054> SETJY1: **WARNING: OPCODE=CALC AND FREQID = -1
vlb054> SETJY1: FREQID WILL BE RESET TO 1, CHECK YOUR RESULTS CAREFULLY
vlb054> SETJY1: A source model for this calibrator may be available
vlb054> SETJY1: Use the verb CALDIR to see if there is one
vlb054> SETJY1: / Flux calculated using known spectrum
vlb054> SETJY1: BIF = 1 EIF = 1 /Range of IFs

```

```
vlb054> SETJY1: '3C286' IF = 1 FLUX =14.5979 (Jy calcd)
vlb054> SETJY1: / Using (1990) VLA or Reynolds (1934-638) coefficients
vlb054> SETJY1: Appears to have ended successfully
vlb054> SETJY1: vlb054 31DEC08 TST: Cpu= 0.0 Real= 0
```

CALRD

```
task 'calrd'
object '3c286'
band 'l'
go
```

```
vlb054> CALRD1: Task CALRD (release of 31DEC08) begins
vlb054> CALRD1: Reading disk file AIPSTARS:3C286_L.MODEL
vlb054> CALRD1: Create 3C286_L .MODEL . 1 (MA) on disk 1 cno 5
vlb054> CALRD1: Appears to have ended successfully
vlb054> CALRD1: vlb054 31DEC08 TST: Cpu= 0.0 Real= 0
```

So it looks like the calibration data image was put into catalog entry number 5.

CALIB

```
task 'calib'
getn 2
calsour '3c286',' '
uvrange 0
antennas 0
refant 24
weightit 1
in2di 1
get2n 5
ncomp 0
solmode 'A&P'
aparm(6) 2
minamper 10
minphser 10
docalib 1
solint 1
solsub 2
cparm(3) 10
cparm(4) 10
```

From:

<https://www.astron.nl/lofarwiki/> - **LOFAR Wiki**

Permanent link:

https://www.astron.nl/lofarwiki/doku.php?id=public:meetings:glowbi2008:tutorial_monday&rev=1226695271

Last update: **2008-11-14 20:41**

